

PORTABLE POWER STATION 1000W



YoHoo elec

www.yohooelec.com

@yohoo_elec      

Portable Power Station



 **TV**
14 Hours (60W)

 **Refrigerator**
22 Hours (40W)

 **Wifi**
179 Hours (5W)

 **Lighting**
89 Hours (10W)

 **CCTV**
29 Hours (30W)

 **Electric fan**
35 Hours (25W)

 **Computer**
18 Hours (50W)

 **Phone**
97 Times (18W)

Technical Indicators(BPS-1000F)

Parameters

Battery energy	1120Wh
AC Output Nominal Voltage	230V 50Hz
AC Output Nominal Power	1000W(instantaneous peak power 2000W)
DC Output TYPE-C Output	5V/3A,9V/3A,12V/3A,15V/3A,20V/5A 100W MAX
DC Output TYPE-C Output	5V/3A,9V/3A,12V/2.5A,15V/2A,20V/1.5A 30W MAX
DC Output USB 3.0 Output	5V/3A,9V/2A,12V/1.5A 18W MAX
DC Output	12V*5A
Wireless charging Output	15W MAX
Cigarette lighter Output	12V*10A
Flashlight	brightness, Common brightness , Highbrightness, SOS-Slow or Fast blinking
AC Discharge Period Running a load of 1000W	About 55 minutes
Operating Temperature	14~104°F
Dimensions	321X235X286mm
Net Weight	About 12kg

*All the data above are collected through experiments.